

## ASR-3000 Series



### FEATURES

- \* Output Rating: AC 0 ~ 400 Vrms, DC 0 ~ ± 570 V
- \* Output Frequency up to 999.9 Hz
- \* DC Output (100% of Rated Power)
- \* Measurement Items: Vrms, Vavg, Vpeak, Irms, IpkH, Iavg, Ipeak, P, S, Q, PF, CF
- \* Voltage and Current Harmonic Analysis(THDv, THDi)
- \* Remote Sensing Capability
- \* OCP, OPP, OTP, AC Fail Detection and Fan Fail Alarm
- \* Support Arbitrary Waveform Function
- \* Output Capacity: 2kVA/ 3kVA/4kVA
- \* Customized Phase Angle for Output On/Off
- \* Sequence and Simulation Function (up to 10 sets)
- \* Interface(std):USB,LAN,RS-232,GPIB
- \* Built-in External Control I/O and External Signal Input
- \* Built-in Output Relay Control
- \* Memory Function (up to 10 sets)
- \* Built-in Web Server



The ASR-3000 Series is an AC+DC power source, featuring high-speed DC voltage rising and falling time ( $\leq 100\mu s$ ). There are three models of the series: ASR-3200(2kVA), ASR-3300(3kVA) and ASR-3400 (4kVA). The series can provide rated power output during AC output and DC output. Ten ASR-3000 Series output modes are available, including 1) AC power output mode (AC-INT Mode), 2) DC power output mode (DC-INT Mode), 3) AC/DC power output mode (AC+DC-INT Mode), 4) External AC signal source mode (AC-EXT Mode), 5) External AC/DC signal source mode (AC+DC-EXT Mode), 6) External AC signal superimposition mode (AC-ADD Mode), 7) External AC/DC signal superimposition mode (AC+DC-ADD Mode), 8) External AC signal synchronization mode (AC-SYNC Mode), 9) External AC/DC signal synchronization mode (AC+DC-SYNC Mode), 10) External DC voltage control of AC output mode(AC-VCA).

ASR-3000 Series is ideal for the development of On-board Chargers, Server Powers, LED modules, AC Motors, AC Fans, UPS and various electronic components, as well as for testing applications of automotive electrical equipment and home appliances.

The ASR-3000 Series provides users with waveform output capabilities including 1) Sequence mode generates waveform fallings, surges, sags, changes and other abnormal power line conditions; 2) Arbitrary waveform function allows users to store/upload user-defined waveforms; and 3) Simulate mode simulates power outage, voltage rise, voltage fall, and frequency variations. When the ASR-3000 Series power source outputs, it can also measure Vrms, Vavg, Vpeak, Irms, Iavg, Ipeak, IpkH, P, S, Q, PF, CF, 100th-order Voltage Harmonic and Current Harmonic. In addition, the remote sensing function ensures accurate voltage output, and the Customized Phase Angle for Output On/Off function can set the start and end angles of the voltage output according to the test requirements. The protection limits of V-Limit, Ipeak-Limit and F-Limit can be set according to user requirements. Over voltage limit, OCP, OPP will protect the DUT during the output process. The Fan Fail Alarm function and the AC fail alarm function are also designed in the ASR-3000 Series.

The front panel of the ASR-3000 Series provides a universal socket or a European socket, which allows users to plug and use so as to save wiring time. Since the power socket specification has a maximum current of 15A, the rear panel of ASR-3000 Series is designed with a current circuit breaker. When the socket current is greater than 15A, it will automatically open the circuit to protect users. The ASR-3000 Series supports I/O interface and is standardly equipped with USB, LAN, External I/O, RS-232C and GPIB.



Front Panel



Rear Panel

### APPLICATIONS

- Electronic Products/Electronic Component Development test
- Automotive Electrical Device Simulation Test
- Household Appliance Application Test
- On-board Chargers
- Server Powers, LED Modules, AC Motors, AC Fans, UPS

Model	ASR-3200	ASR-3300	ASR-3400
Output Voltage	0~400Vrms/0~±570Vdc	0~400Vrms/0~±570Vdc	0~400Vrms/0~±570Vdc
Output Current	20/10A	30/15A	40/20A
Power Rating	2000VA	3000VA	4000VA
Output Frequency	1.00Hz ~ 999.9Hz	1.00Hz ~ 999.9Hz	1.00Hz ~ 999.9Hz

**SPECIFICATIONS**

	ASR-3200	ASR-3300	ASR-3400
<b>INPUT RATING (AC)</b>			
<b>NORMAL INPUT VOLTAGE</b>	200 Vac to 240 Vac	200 Vac to 240 Vac	200 Vac to 240 Vac
<b>INPUT VOLTAGE RANGE</b>	180 Vac to 264 Vac	180 Vac to 264 Vac	180 Vac to 264 Vac
<b>PHASE</b>	Single phase, Two-wire	Single phase, Two-wire	Single phase, Two-wire
<b>NORMAL INPUT FREQUENCY</b>	50 Hz to 60 Hz	50 Hz to 60 Hz	50 Hz to 60 Hz
<b>INPUT FREQUENCY RANGE</b>	47 Hz to 63 Hz	47 Hz to 63 Hz	47 Hz to 63 Hz
<b>MAX. POWER CONSUMPTION</b>	2500 VA or less	3750 VA or less	5000 VA or less
<b>POWER FACTOR<sup>1</sup></b>	200Vac	0.95 (TYP)	0.95 (TYP)
<b>MAX. INPUT CURRENT</b>	200Vac	15 A	30 A

\*1. For an output voltage of 100 V/200 V (100V/200V range), maximum current, and a load power factor of 1.

<b>AC MODE OUTPUT RATINGS (AC rms)</b>			
<b>VOLTAGE</b>	<b>Setting Range<sup>1</sup></b> <b>Setting Resolution</b> <b>Accuracy<sup>2</sup></b>	0.0 V to 200.0 V / 0.0 V to 400.0 V 0.1 V ±(1 % of set + 1 V / 2 V) Single phase, Two-wire	
<b>OUTPUT PHASE</b>			
<b>MAXIMUM CURRENT<sup>3</sup></b>	<b>100 V</b> <b>200 V</b>	20 A 10 A	30 A 15 A
<b>MAXIMUM PEAK CURRENT<sup>4</sup></b>	<b>100 V</b> <b>200 V</b>	120 A 60 A	180 A 90 A
<b>LOAD POWER FACTOR</b>		0 to 1 (leading phase or lagging phase)	
<b>POWER CAPACITY</b>		2000 VA	3000 VA
<b>FREQUENCY</b>	<b>Setting Range</b> <b>Setting Resolution</b> <b>Accuracy</b> <b>Stability<sup>5</sup></b>	AC Mode: 40.00 Hz to 999.9 Hz, AC+DC Mode: 1.00 Hz to 999.9 Hz 0.01 Hz (1.00 to 99.99 Hz), 0.1 Hz (100.0 to 999.9 Hz) 0.02% of set (23 °C ± 5 °C) ± 0.005% 0° to 359° variable (setting resolution 1°) Within ± 20 mV (TYP)	
<b>OUTPUT ON PHASE</b>	<b>DC OFFSET<sup>6</sup></b>		

\*1. 100 V / 200 V range \*2. For an output voltage of 20 V to 200 V / 40 V to 400 V, an output frequency of 45 Hz to 65 Hz, no load, and 23 °C ± 5 °C  
\*3. For an output voltage of 1 V to 100 V / 2 V to 200 V. Limited by the power capacity when the output voltage is 100 V to 200 V / 200 V to 400 V. If there is the DC superimposition, the current of AC+DC mode satisfies the maximum current. In the case of lower than 40 Hz, and the power rating temperature, the maximum current will be decrease.  
\*4. With respect to the capacitor-input rectifying load. Limited by the maximum current.  
\*5. For 45 Hz to 65 Hz, the rated output voltage, no load and the resistance load for the maximum current, and the operating temperature. \*6. In the case of the AC mode and 23 °C ± 5 °C.

<b>OUTPUT RATING FOR DC MODE</b>			
<b>VOLTAGE</b>	<b>Setting Range<sup>1</sup></b> <b>Setting Resolution</b> <b>Accuracy<sup>2</sup></b>	-285 V to + 285 V / -570 V to +570 V 0.1 V ±(1 % of set + 1 V / 2 V)	
<b>MAXIMUM CURRENT<sup>3</sup></b>	<b>100 V</b> <b>200 V</b>	20 A 10 A	30 A 15 A
<b>MAXIMUM PEAK CURRENT<sup>4</sup></b>	<b>100 V</b> <b>200 V</b>	120 A 60 A	180 A 90 A
<b>POWER CAPACITY</b>		2000 W	3000 W

\*1. 100 V / 200 V range \*2. For an output voltage of -285 V to +285 V, -570 V to +570 V, no load, and 23 °C ± 5 °C  
\*3. For an output voltage of 1.4 V to 100 V / 2.8 V to 200 V. Limited by the power capacity when the output voltage is 100 V to 250 V / 200 V to 500 V. \*4. Limited by the maximum current.

<b>OUTPUT VOLTAGE STABILITY</b>	
<b>LINE REGULATION<sup>1</sup></b>	±0.2% or less
<b>LOAD REGULATION<sup>2</sup></b>	0.5% or less (0 to 100%, via output terminal)
<b>RIPPLE NOISE<sup>3</sup></b>	1 Vrms / 2 Vrms (TYP)

\*1. Power source input voltage is 200 V, 220 V, or 240 V, no load, rated output. \*2. For an output voltage of 100 V to 200 V / 200 V to 400 V, a load power factor of 1, stepwise change from an output current of 0 A to maximum current (or its reverse), using the output terminal on the rear panel. \*3. For 5 Hz to 1 MHz components in DC mode using the output terminal on the rear panel.

<b>OUTPUT VOLTAGE WAVEFORM DISTORTION RATIO, OUTPUT VOLTAGE RESPONSE TIME, EFFICIENCY</b>	
<b>TOTAL HARMONIC DISTORTION (THD)<sup>1</sup></b>	≤ 0.2% @50/60Hz, ≤ 0.3% @<500Hz, ≤ 0.5% @500.1Hz~999.9Hz
<b>OUTPUT VOLTAGE RESPONSE TIME<sup>2</sup></b>	100 us (TYP)
<b>EFFICIENCY<sup>3</sup></b>	80 % or more

\*1. At an output voltage of 50 V to 200 V / 100 V to 400 V, a load power factor of 1, and in AC mode. \*2. For an output voltage of 100 V / 200 V, a load power factor of 1, with respect to stepwise change from an output current of 0 A to the maximum current (or its reverse). \*3. For AC mode, at an output voltage of 100 V / 200 V, maximum current, and load power factor of 1.

<b>MEASURED VALUE DISPLAY</b>			
<b>VOLTAGE</b>	<b>RMS, AVG Value<sup>1</sup></b>	<b>Resolution</b> <b>Accuracy<sup>2</sup></b>	0.1 V For 45 Hz to 65 Hz and DC: ±(0.5 % of reading + 0.5 V/1 V); For all other frequencies: ±(0.7 % of reading + 1 V / 2 V)
	<b>PEAK Value</b>	<b>Resolution</b> <b>Accuracy</b>	0.1 V For 45 Hz to 65 Hz and DC: ±( 2 % of reading  + 1 V / 2 V)
<b>CURRENT</b>	<b>RMS, AVG Value</b>	<b>Resolution</b> <b>Accuracy<sup>3</sup></b>	0.01 A For 45 Hz to 65 Hz and DC: ±(0.5 % of reading+0.1 A/0.05 A); For all other frequencies: ±(0.7 % of reading+0.2 A/0.1 A)
	<b>PEAK Value</b>	<b>Resolution</b> <b>Accuracy<sup>4</sup></b>	0.01 A/0.1 A For 45 Hz to 65 Hz and DC: ±( 2 % of reading  + 0.5 A/0.25 A)
<b>POWER</b>	<b>Active (W)</b>	<b>Resolution</b> <b>Accuracy<sup>5</sup></b>	1 W ±(2 % of reading + 2 W)
	<b>Apparent (VA)</b>	<b>Resolution</b> <b>Accuracy<sup>5*6</sup></b>	1 VA ±(2 % of reading + 3 W)
	<b>Reactive (VAR)</b>	<b>Resolution</b> <b>Accuracy<sup>5*7</sup></b>	1 VAR ±(2 % of reading + 3 VA)
<b>LOAD POWER FACTOR</b>	<b>Range</b>	<b>Resolution</b>	±(2 % of reading + 2 VAR) 0.000 to 1.000 0.001
<b>LOAD CREST FACTOR</b>	<b>Range</b>	<b>Resolution</b>	0.00 to 50.00 0.01
<b>HARMONIC VOLTAGE</b>	<b>Range</b>	<b>Resolution</b>	Up to 100th order of the fundamental wave 200 V / 400 V, 100% 0.1 V, 0.1%
<b>EFFECTIVE VALUE (RMS)</b>	<b>Full Scale</b>	<b>Resolution</b> <b>Accuracy<sup>8</sup></b>	Up to 20th±(0.2 % of reading+0.5 V/1 V); 20th to 100th±(0.3 % of reading+0.5 V/1 V)
<b>PERCENT (%)</b>	<b>Resolution</b>	<b>Accuracy<sup>8</sup></b>	Up to 100th order of the fundamental wave 20 A / 10 A, 100% 0.01 A, 0.1A, 0.1%
<b>HARMONIC CURRENT</b>	<b>Range</b>	<b>Resolution</b>	Up to 20th±(1% of reading+0.4A/0.2A); 20th to 100th±(1.5% of reading+0.4A/0.2A)
<b>EFFECTIVE VALUE (RMS)</b>	<b>Full Scale</b>	<b>Resolution</b>	0.01 A, 0.1A, 0.1%
<b>PERCENT (%)</b>	<b>Resolution</b>	<b>Accuracy<sup>9</sup></b>	Up to 20th±(1% of reading+0.6A/0.3A); 20th to 100th±(1.5% of reading+0.6A/0.3A)

\*1. The voltage display is set to RMS in AC/AC+DC mode and AVG in DC mode. \*2. AC mode: For an output voltage of 20 V to 200 V / 40 V to 400 V and 23 °C ± 5 °C. DC mode: For an output voltage of 28.5 V to 285 V / 57 V to 570 V and 23 °C ± 5 °C. \*3. An output current in the range of 5 % to 100 % of the maximum peak current in AC mode, an output current in the range of 5 % to 100 % of the maximum instantaneous current in DC mode, and 23 °C ± 5 °C.  
\*4. An output current in the range of 5 % to 100 % of the maximum peak current in AC mode, an output current in the range of 5 % to 100 % of the maximum instantaneous current in DC mode, and 23 °C ± 5 °C.  
\*5. The accuracy of the peak value is for a waveform of DC or sine wave.  
\*6. For an output voltage of 50 V or greater, an output current in the range of 10 % to 100 % of the maximum current, DC or an output frequency of 45 Hz to 65 Hz, and 23 °C ± 5 °C.  
\*7. The apparent and reactive powers are not displayed in the DC mode. \*8. The reactive power is for the load with the power factor 0.5 or lower.  
\*9. An output voltage in the range of 20 V to 200 V / 40 V to 400 V and 23 °C ± 5 °C.

<b>OTHERS</b>	
<b>PROTECTIONS</b>	UVP, OCP, OTP, OPP, FAN Fail
<b>DISPLAY</b>	TFT-LCD, 4.3 inch
<b>MEMORY FUNCTION</b>	Store and recall settings, Basic settings: 10 (0-9 numeric keys)
<b>ARBITRARY WAVE</b>	Number of Memories: 16 (nonvolatile) Waveform Length: 4096 words
<b>INTERFACE</b>	<b>Standard</b> <b>USB</b> <b>LAN</b> <b>RS-232C</b> <b>EXT Control</b> <b>GPIO</b>
<b>INSULATION RESISTANCE</b>	500 Vdc, 30 MΩ or more
<b>WITHSTAND VOLTAGE</b>	1500 Vac, 1 minute
<b>EMC</b>	EN 61326-1, EN 61326-2-1, EN 61000-3-2, EN 61000-3-3, EN 61000-3-11, EN 61000-3-12, EN 61000-4-2/-4-3/-4-4/-4-5/-4-6/-4-8/-4-11/-4-34, EN 55011 (Class A), EN 55032
<b>Safety Environment</b>	<b>Operating Environment</b> Indoor use, Overvoltage Category II <b>Operating Temperature Range</b> 0 °C to 40 °C <b>Storage Temperature Range</b> -10 °C to 70 °C <b>Operating Humidity Range</b> 20 % RH to 80 % RH (no condensation) <b>Storage Humidity Range</b> 90 % RH or less (no condensation) <b>Altitude</b> Up to 2000 m
<b>DIMENSIONS &amp; WEIGHT</b>	430(W)×176(H)×530(D)mm (not including protrusions); Approx. 25 kg

Specifications subject to change without notice. ASR-3000CD1DH

<b>ORDERING INFORMATION</b>	
<b>ASR-3200</b>	2kVA Programmable AC/DC Power Source
<b>ASR-3300</b>	3kVA Programmable AC/DC Power Source
<b>ASR-3400</b>	4kVA Programmable AC/DC Power Source
<b>ACCESSORIES</b>	
CD (User Manual/Programming Manual), Safety Guide, Input Terminal Cover, Output Terminal Cover Include Remote Sensing, CRA-442-E Rack Mount Adapter(EIA), GTL-246 USB Cable	

<b>OPTIONAL ACCESSORIES</b>	
<b>GPW-005</b>	Power Cord, 3m, 105°C, UL/CSA Type
<b>GPW-006</b>	Power Cord, 3m, 105°C, VDE Type
<b>GPW-007</b>	Power Cord, 3m, 105°C, PSE Type
<b>GRA-442-J</b>	Rack Mount Adapter (JIS)
<b>GTL-137</b>	Output Power Wire (Load wire_10AWG; 50A, 600V/ Sense wire_16AWG; 20A, 600V)
<b>GTL-232</b>	RS232C cable, approx. 2m
<b>GTL-248</b>	GPIO Cable, approx. 2m
<b>ASR-002</b>	External Three Phase Control Unit
<b>APS-008</b>	Air inlet filter

\* With respect to ASR-002, please refer to the brochure or website for detail. \* European Output Outlet(factory installed)

Combined Test Solutions,  
4 Commerce Way, Stanbridge Road,  
Leighton Buzzard, LU7 4RW

T: 01525 374466  
E: [sales@ctstest.co.uk](mailto:sales@ctstest.co.uk)  
W: [www.ctstest.co.uk](http://www.ctstest.co.uk)

